


INSTALLATION INSTRUCTIONS

LLW-3C-40K-U | LLW-4C-40K-U | LLW-5C-40K-U
LLW - LED Linear Wrap



SAFETY PRECAUTION:

To reduce the risk of death, personal injury or property damage from fire, electric shock, falling parts, cuts/abrasions, and other hazards read all warnings and instructions included with and on the fixture box and all fixture labels.

Before installing, servicing, or performing routine maintenance upon this equipment, follow these general precautions. Commercial installation, service and maintenance of luminaires should be performed by a qualified licensed electrician. For The installation: If you are unsure about the installation or maintenance of the luminaires, consult a qualified licensed electrician and check your local electrical code.

To prevent wiring damage or abrasion, do not expose wiring to edges of sheet metal or other sharp objects. Do not make or alter any open holes in an enclosure of wiring or electrical components during kit installation.

WARNING: RISK OF FIRE OR ELECTRICAL SHOCK

Turn off electrical power at fuse or circuit breaker box before wiring fixture to the power supply. Turn off the power when you perform any maintenance.

Verify that supply voltage is correct by comparing it with the luminaire label information.

Make all electrical and grounded connections in accordance with the National Electrical Code and any applicable local code requirements.

All wiring connections should be capped with UL approved wire connectors.

CAUTION: RISK OF INJURY

Avoid direct eye exposure to the light source while it is on.

Account for small parts and destroy packing material, as these may be hazardous to children.

Risk of burns. Disconnect power and allow fixture to cool before chaging bulb or handling fixture.

SUITABLE FOR DRY OR DAMP LOCATION

GREEN GROUND SCREW PROVIDED IN PROPER LOCATION. DO NOT RELOCATE.

MINIMUM 90° SUPPLY CONDUCTORS.

SPECIFICATIONS AND DIMENSIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE.

INSTALLATION:

BEFORE INSTALLATION, ENSURE THAT POWER SUPPLY IS DISCONNECTED. CABLES MUST BE CONNECTED IN ACCORDANCE TO INSTRUCTION AND PROPER STANDING RULES.

1. Remove product from packaging.
2. Removed lens by pulling from one side of the fixture and hinge on the other.
3. Remove the driver cover.
4. For mounting, using the provided mounting holes on each end of the fixture housing.
5. Make electrical connections according to code.
6. Install channel cover.
7. Install lens on one side fo the fixture and rotate to engage the opposite side.

